

CONFIDENTIAL

CLAIMS

What is claimed is:

1. A low current oscillator circuit, comprising:
 - 5 a comparator for driving an output signal;
 - a first capacitor chain coupled to the comparator and for setting a first input voltage of the comparator; and
 - a second capacitor chain coupled to the comparator and for setting a second input voltage of the comparator, wherein the first
 - 10 capacitor chain and the second capacitor chain determine a first voltage level and a second voltage level of oscillation of the comparator free of DC current flow.
2. The low current oscillator circuit of claim 1, further
15 comprising:
 - a switch circuit coupled to the comparator and for initiating an oscillation in the comparator.
3. The low current oscillator circuit of claim 2, further
20 comprising:
 - a feedback circuit coupled to an output of the comparator, the feedback circuit also coupled to the switch circuit for driving the switch circuit.
4. The low current oscillator circuit of claim 2, further
25 comprising:
 - a capacitor included in the switch circuit;
 - a current source coupled to capacitor and for charging the capacitor to the high voltage; and

CONFIDENTIAL

a switch coupled to the capacitor for discharging the capacitor to the low voltage.

5. The low current oscillator circuit of claim 1, further comprising:

a first capacitor and a second capacitor included in the first capacitor chain; and

a third capacitor and a fourth capacitor included in the second capacitor chain, wherein a node between the first capacitor and the second capacitor determines the first voltage level of oscillation and a node between the third capacitor and the fourth capacitor determines the second voltage level of oscillation.

6. An integrated circuit system including a low current oscillator circuit, comprising:

a comparator for driving an output signal;

a first capacitor chain coupled to the comparator and for setting a first input voltage of the comparator;

a second capacitor chain coupled to the comparator and for setting a second input voltage of the comparator, wherein the first capacitor chain and the second capacitor chain determine a first voltage level and a second voltage level of oscillation of the comparator free of DC current flow; and

an output signal line coupled to an output of the comparator for providing an oscillation signal to external circuit elements of the integrated circuit system.

7. The integrated circuit system of claim 6, further comprising:

CONFIDENTIAL

a switch circuit coupled to the comparator and for initiating an oscillation in the comparator.

5 8. The integrated circuit system of claim 7, further comprising:
a feedback circuit coupled to an output of the comparator, the
feedback circuit also coupled to the switch circuit for driving the switch
circuit.

10 9. The integrated circuit system of claim 7, further comprising:
a capacitor included in the switch circuit;
a current source coupled to capacitor and for charging the
capacitor to the high voltage; and
a switch coupled to the capacitor for discharging the capacitor to
the low voltage.

15 10. The integrated circuit system of claim 6, further comprising:
a first capacitor and a second capacitor included in the first
capacitor chain; and
a third capacitor and a fourth capacitor included in the second
20 capacitor chain, wherein a node between the first capacitor and the
second capacitor determines the first voltage level of oscillation and a
node between the third capacitor and the fourth capacitor determines
the second voltage level of oscillation.

25 11. A low current oscillator circuit, comprising:
means for driving an output signal using a comparator;
means for setting a first input voltage of the comparator using a
first capacitor chain coupled to the comparator; and

CONFIDENTIAL

means for setting a second input voltage of the comparator using a second capacitor chain coupled to the comparator, wherein the first capacitor chain and the second capacitor chain determine a first voltage level and a second voltage level of oscillation of the comparator
5 free of DC current flow.

12. The low current oscillator circuit of claim 11, further comprising:

means for initiating an oscillation in the comparator using a
10 switch circuit coupled to the comparator.

13. The low current oscillator circuit of claim 12, further comprising:

means for driving the switch circuit using a feedback circuit
15 coupled to an output of the comparator, the feedback circuit also coupled to the switch circuit.

14. The low current oscillator circuit of claim 12, further comprising:

20 a capacitor included in the switch circuit;

means for charging the capacitor to the high voltage using a current source coupled to capacitor; and

means for discharging the capacitor to the low voltage using a switch coupled to the capacitor.

25

15. The low current oscillator circuit of claim 11, further comprising:

a first capacitor and a second capacitor included in the first capacitor chain; and

CONFIDENTIAL

a third capacitor and a fourth capacitor included in the second capacitor chain, wherein a node between the first capacitor and the second capacitor determines the first voltage level of oscillation and a node between the third capacitor and the fourth capacitor determines
5 the second voltage level of oscillation.

16. The low current oscillator circuit of claim 15, wherein a first ratio of the first capacitor and the second capacitor determines the first voltage level and a second ratio of the third capacitor and the fourth
10 capacitor determines the second voltage level.

17. The low current oscillator of claim 11, further comprising:
means for determining a duty cycle of an oscillation in the
comparator using a switch circuit coupled to the comparator.